






Techup e. U.  
Tenschertstrasse 5/ 1 Stock  
A-1230 Wien - Austria

Tel.: +43-(0)1 61 50 499-88  
Fax: +43-(0)1 61 50 499-89  
E-mail: yue@techup.at  
Webseite: www.techup.at

## LED AR111 Leuchtmitteln

(AC/DC12V od. GU10 100-240VAC)

Picture	Model No.	LED Power	Luminous (lm)	Beam Angle	Input Voltage	Base	Dimmable	Chips Brand	Packing details
	AR111-6W-B	6X1W	390~460Lm	25/40/60/140	AC/DC 12V	G53	N	Bridgelux	30pcs/CTN 58.5X36X18 cm
	AR111-6WD-B			25/40/60/140	AC110/220V	G53	Y		
	AR111-6W-C			25	AC/DC 12V	G53	N	Cree XPE	
	AR111-6WD-C			25	AC110/220V	G53	Y		
Picture	Model No.	LED Power	Luminous (lm)	Beam Angle	Input Voltage	Base	Dimmable	Chips Brand	Packing details
	AR111-12W-B	6X2W	600~680Lm	25/40/60/140	AC/DC 12V	G53	N	Bridgelux	30pcs/CTN 58.5X36X18 cm
	AR111-12WD-B			25/40/60/140	AC110/220V	G53	Y		
	AR111-12W-C			25	AC/DC 12V	G53	N	Cree XPE	
	AR111-12WD-C			25	AC110/220V	G53	Y		
Picture	Model No.	LED Power	Luminous (lm)	Beam Angle	Input Voltage	Base	Dimmable	Chips Brand	Packing details
	AR111-9W-B	9X1W	600~670Lm	30/45/60	AC/DC 12V	G53	N	Bridgelux	30pcs/CTN 58.5X36X18 cm
	AR111-9WD-B			30/45/60	AC110/220V	G53	Y		
	AR111-9W-C			25	AC/DC 12V	G53	N	Cree XRE	
	AR111-9WD-C			25	AC110/220V	G53	Y		
Picture	Model No.	LED Power	Luminous (lm)	Beam Angle	Input Voltage	Base	Dimmable	Chips Brand	Packing details
	AR111-12W-SCOB***	12W	600~750Lm	25	30/45/60	G53	N	Bridgelux SCOB	48pcs/CTN 51.2X38.8X 45.8cm
Picture	Model No.	LED Power	Luminous (lm)	Beam Angle	Input Voltage	Base	Dimmable	Chips Brand	Packing details
	AR111-GU10-15W	15W	White : 730~750Lm Warm white : 610~630Lm	15/30	100-240VAC	GU10	N	Citizen	30pcs/CTN 58.5X36X18 cm

\*\*\* SCOB = Stereoscopic Chip On Board